

**Second Hall has the same setup for FOH and Monitors.**

**2x the following:**

- \_ **1x L200** (mixingdesk)
- \_ **2x SB32.24** (I/O box, together analog 64in - 32out, AES/EBU 8in - 8out)
- \_ **1x computer with Solsa** (SSL Offline Setup Application); at the monitorposition we have a tablet, so it's possible to connect and control the desk wireless. The FOH-position has an extra bracket for a laptop.

**The Desk and I/O boxes are connected with a Dante system. Because off that all SSL equipment work on a samplerate of 48 kHz.**

**So both desks have their own I/O boxes (2x SB32.24), totally separate control of the in- and outputs.**

**The SB32.24's (4x) are offstage. Patching to these SB32.24's is possible with the Onstage Patchbox, in which the FOH and Monitor SB32.24's are represented.**

- \_ **64x Onstage Input**, paralel to FOH and Monitors
- \_ **16x Onstage Output from FOH**
- \_ **24x Onstage Output from Monitors**
- \_ **8x In, 8x Out AES/EBU from FOH**
- \_ **8x In, 8x Out AES/EBU from Monitors**
- \_ **4x ethernet socket (Dante)**
- \_ **12x XLR Male/Female (TIE Line FOH)**

**For both positions there are Base Showfiles ("PAT...BASE").**

**When a Showfile is selected, you can find configuration-information at the bottom of the screen. It gives usefull information of the setup.**

#### **\_NOTES**

**We tried to prepare all common connections in the "PAT...BASE" Showfiles.**

**If you want to prepare a Showfile in Solsa, make sure you choose L200!**

**It is possible to configure the L200 the way you want to. (Menu>Setup> Console Configuration). Whatch the blue usage bars at the top of the screen.**

**You can make several Scenes within a Showfile. Setup changes affect all Scenes within the Showfiles! For instance, making a stereochannel, happens in all Scenes, at that spot.**

**We think it is helpfull to build the desk in a chronological order.**

**Solsa (SSL Offline Setup Application) is available at the SSL website.**

**[solidstatellogic.com](http://solidstatellogic.com)**

**It's a heavy program, which gives some problems on a light computer (Windows). TO IMPORT A FILE YOU HAVE TO USE A STICK, JUST AS THE REAL DESK.**